

■ Combinations meeting for UL market

• **BM3RSB, BM3RHB**

3-phase motor				Manual motor starters		Adjustable current range (A)	Magnetic contactor	Link module	Base plate
Rated capacity (HP) 220–240V AC	Rated operational current (A)	Rated capacity (HP) 440–480V AC	Rated operational current (A)						
–	–	–	–	BM3RSB-P16	BM3RHB-P16	0.1 to 0.16	SC-M01	BZ0LRC09AA	–
							SC-E02	BZ0LRE22AA	BZ0BPVE22A
–	–	–	–	BM3RSB-P25	BM3RHB-P25	0.16 to 0.25	SC-M01	BZ0LRC09AA	–
							SC-E02	BZ0LRE22AA	BZ0BPVE22A
–	–	–	–	BM3RSB-P40	BM3RHB-P40	0.25 to 0.4	SC-M01	BZ0LRC09AA	–
							SC-E02	BZ0LRE22AA	BZ0BPVE22A
–	–	–	–	BM3RSB-P63	BM3RHB-P63	0.4 to 0.63	SC-M01	BZ0LRC09AA	–
							SC-E02	BZ0LRE22AA	BZ0BPVE22A
–	–	–	–	BM3RSB-001	BM3RHB-001	0.63 to 1.0	SC-M01	BZ0LRC09AA	–
							SC-E02	BZ0LRE22AA	BZ0BPVE22A
–	–	0.75	1.6	BM3RSB-1P6	BM3RHB-1P6	1.0 to 1.6	SC-M01	BZ0LRC09AA	–
							SC-E02	BZ0LRE22AA	BZ0BPVE22A
0.5	2.2	1	2.1	BM3RSB-2P5	BM3RHB-2P5	1.6 to 2.5	SC-M01	BZ0LRC09AA	–
							SC-E02	BZ0LRE22AA	BZ0BPVE22A
0.75	3.2	2	3.4	BM3RSB-004	BM3RHB-004	2.5 to 4	SC-M01	BZ0LRC09AA	–
							SC-E02	BZ0LRE22AA	BZ0BPVE22A
1.5	6	3	4.8	BM3RSB-6P3	BM3RHB-6P3	4 to 6.3	SC-M01	BZ0LRC09AA	–
							SC-E02	BZ0LRE22AA	BZ0BPVE22A
–	–	5	7.6	BM3RSB-010	BM3RHB-010	6.3 to 10	SC-M02	BZ0LRC09AA	–
							SC-E02	BZ0LRE22AA	BZ0BPVE22A
3	9.6	7.5	11	BM3RSB-013	BM3RHB-013	9 to 13	SC-E03	BZ0LRE22AA	BZ0BPVE22A
5	15.2	10	14	BM3RSB-016	BM3RHB-016	11 to 16	SC-E04	BZ0LRE22AA	BZ0BPVE22A
5	15.2	10	14	BM3RSB-020	BM3RHB-020	14 to 20	SC-E04	BZ0LRE22AA	BZ0BPVE22A
7.5	22	15	21	BM3RSB-025	BM3RHB-025	19 to 25	SC-E05	BZ0LRE22AA	BZ0BPVE22A
10	28	20	27	BM3RSB-032	BM3RHB-032	24 to 32	SC-E1	BZ0LRE32AA	BZ0BPVE32A

• **BM3VSB, BM3VHB**

3-phase motor				Manual motor starters		Adjustable current range (A)	Magnetic contactor	Link module	Base plate
Rated capacity (HP) 220–240V AC	Rated operational current (A)	Rated capacity (HP) 440–480V AC	Rated operational current (A)						
3	9.6	5	7.6	BM3VSB-010	BM3VHB-010	6.3 to 10	SC-E1	BZ0LVE51AA	BZ0BPVE51A
3	9.6	7.5	11	BM3VSB-013	BM3VHB-013	9 to 13	SC-E1	BZ0LVE51AA	BZ0BPVE51A
5	15.2	10	14	BM3VSB-016	BM3VHB-016	11 to 16	SC-E1	BZ0LVE51AA	BZ0BPVE51A
5	15.2	10	14	BM3VSB-020	BM3VHB-020	14 to 20	SC-E1	BZ0LVE51AA	BZ0BPVE51A
7.5	22	15	21	BM3VSB-025	BM3VHB-025	19 to 25	SC-E1	BZ0LVE51AA	BZ0BPVE51A
10	28	20	27	BM3VSB-032	BM3VHB-032	24 to 32	SC-E1	BZ0LVE51AA	BZ0BPVE51A
10	28	30	40	BM3VSB-040	BM3VHB-040	28 to 40	SC-E2	BZ0LVE51AA	BZ0BPVE51A
15	42	30	40	BM3VSB-050	BM3VHB-050	35 to 50	SC-E2S	BZ0LVE51AA	BZ0BPVE51A
20	54	40	52	BM3VSB-063	BM3VHB-063	45 to 63	SC-E3	BZ0LVE65AA	BZ0BPVE65A